

Buffalo Inverter

اینورتر بوفالو برای کاربردهای خانگی

- در توانهای 600VA,1500VA
- با طراحی هوشمند و مناسب برای منازل و یا دفاتر کوچک با قطع برق مکرر و طولانی
- دستگاهی مطمئن با ظاهری زیبا، بازه گسترده، ولتاژ ورودی
- مناسب دستگاههایی نظیر تلویزیون، یخچال، DVD player، سشوار، دریل برقی، جارو برقی
- دارای کلید انتخاب جریان شارژ 10A/20A، کلید انتخاب حالت UPS و اینورتر
- دارای استابلایزر
- نمایشگرهای باتری در حال شارژ، شارژ کامل، روشن بودن دستگاه، وجود برق شهر، روشن بودن اینورتر

Model		Buffalo 600 600VA/480W	Buffalo 1500 1500VA/1200W
POWER	Voltage	220Vac/Single Phase	
	Voltage Range	On Inverter : 145 to 285 Vac On UPS: 175 to 275 Vac	
	Frequency	50Hz	
Input	Voltage On Mains	On Inverter : 165 to 250 Vac On UPS: 195 to 250 Vac	
	Voltage On Battery	220 Vac±10%	
	Wave form	Sine Wave	
	P.F	0.8	
Output	Overload	YES(AC mode protected by input fuse :Battery mode by electronic circuit)	
	Short circuit	YES(AC mode protected by input fuse :Battery mode by electronic circuit)	
Protection		1.AC mode protected by input fuse 2.Battery ode: 3.1)100~ 110% Output shutdown within 10sec and go into failure mode 2)≥ 110% output shutdown immediately and go into failure mode	
Overload capability			
Noise		≤ 45db(1meter)	
Insulation resistance		>2M(500Vdc)	
Insulation Strength		(Input GND.outputGND)2820Vdc	
Battery Voltage		12V	24V
Charging Voltage		13.8V±0.3V	27.6V±0.6V
Diminsion W *D*H(mm)		235*245*156	258*285*160
Packing W *D*H(mm)		318*326*232	338*366*242
G.W (KG)		10.5	16.5
N.W (KG)		11.5	17.5